

OCIE Cleaning Instruction for Turn-in

The inspection standard for ALL OCIE is as follows:

1. CLEAN
2. DRY (AIR DRIED)
3. FREE OF ODOR
4. FREE OF ANIMAL HAIR
5. FREE OF TAPE AND ADHESIVE
6. FREE OF ANY IDENTIFYING MARKS (Name, Rank, Unit or last 4 of SSN)

1. Bag items



Barracks Bag



Duffle Bag



Waterproof bag

- A. All marking on bag items must be blacken/covered out with permanent marker or spray paint.
- B. Barracks Bag can be laundered via commercial washer and dryer
- C. Duffle bag. Recommended to use soft bristle brush to remove any dirt and stain with mild detergent.
- D. Waterproof bag. Recommended to use a wet cloth to wipe down both sides.

2. ACH Helmet



- A. Remove and disassemble the helmet.
- B. ACH Shell. Clean with mild soap and water. Use a soft brush or cloth.
- C. Chinstrap, Cover, and Pads. Clean with mild soap and water. Wash by hand or in machine in the gentle cycle with cold water.
- D. Allow to air dry. **DO NOT MACHINE DRY!**
- E. Additional guidance provided on Gentex Co. TP0271 REV.2

3. Body Armor / FoCBA



IOTV



Components

- A. Remove and disassemble body armor.
- B. Remove all ballistic / stab panels from carrier.
- C. Machine wash carrier in warm water using mild detergent.
- D. **DO NOT MACHINE WASH BALLISTIC / STAB PANEL. DO NOT USE BLEACH OR APPLY CLEANING SOLVENT. DO NOT SUBMERGE IN WATER OR OTHER LIQUIDS.**
- E. **ONLY** remove dirt from surface and wipe clean with moisten cloth or soft bristle brush.
- F. **DO NOT MACHINE DRY** and avoid heat source and direct sunlight.
- G. Additional guidance provided on TM 10-8470-208-10-PMC
- H. **Assemble** IOTV once it is dry, prior to turn in to CIF

*Gen 3 and Gen 4 IOTV Quick release buckle system carrier cannot be machine washed.

4. Plates



SAPI



E-SAPI



E-SABI

- A. ONLY remove dirt from surface and wipe clean with moisten cloth or soft bristle brush.
- B. DO NOT USE BLEACH OR APPLY CLEANING SOLVENT. DO NOT SUBMERGE IN WATER OR OTHER LIQUIDS

5. Sleeping System & SGI Mat



INTERMEDATE, EXTREME, BIVY, SM STUFF SACK, AND LG STUFF SACK

- A. Sleeping Bag System can be washed in an industrial washing machine and dryer. Not recommend to use commercial machine.
- B. SGI Mat. Deflate mat. ONLY remove dirt from surface and wipe clean with moisten cloth or soft bristle brush.

6. LG. Field Pack



6 COMPONENT SYSTEM

- A. Remove and disassemble Lg. Field Pack
- B. NOT recommended for machine wash.
- C. ONLY remove dirt and stain from surface and wipe clean with moisten cloth or soft bristle brush. Mild detergent made be applied.
- D. Frame. Recommended to use a wet cloth to wipe down.
- E. **Assemble** Field Pack once it is dry, prior to turn in to CIF

7. Rifleman Set



11 COMPONENT SYSTEM

- A. Remove and disassemble Rifleman Set
- B. NOT recommended for machine wash.
- C. Recommended to use soft bristle brush to remove any dirt and stain with mild detergent.

8. Canteen and E-Tool



- A. Canteen. Wipe clean with moisten cloth. Rinse inside with Hot water and mild detergent. Continue till it is odor free. **MUST** be completely free of moisture.
- B. E-tool. Remove all dirt and debris. Respray paint where metal or rust are visible.

9. ECWCS



7 Layer Top and 5 Layer Bottom

- A. All parts of the ECWCS may be machine washed and dry.
- B. Wash in warm water with mild detergent.
- C. Avoid using excessive heat in dryer.

NOTE:

- **If possible, avoid using machine to wash OCIE. Recommend hand washing with soft bristle brush warm or cold water with mild detergent.**
- **Avoid using any softener and allow items to air dry without any direct sunlight.**
- **Do not use any specialty cleaning substance or solutions such as bleach.**
- **Everything that you DISASSEMBLE must be REASSEMBLED prior to turning it in to CIF.**